Concurrency: Theory, Languages and Programming

– Pi Calculus –

Session 6 – November 27, 2002

Uwe Nestmann

EPFL-LAMP

There are (at least) two reasons for studying LTSs
(as opposed to mere reductions as in the λ-calculus):

- the emphasis in on *interaction* with other programs
- redexes$^{(*)}$ in a concurrent program are usually distributed over terms, not juxtaposed as in λ-calculus.

$$(\lambda x.E)F \qquad \overline{a}\langle v\rangle.P_1 \mid (\ P_2 \mid a(x).P_3\ )$$

$(*)$ redexes are the "source" of reductions or internal transitions, visible as the pattern in the conclusion of either the β-rule (in λ) or the COMM-rule (in [VP]CCS).

Unbounded Structures: Stacks (I)

- "specification":
  stored values are encoded in the index of the identifier
  - needs an unbounded number of process identifiers ...
  - does not exploit "concurrency inside"

$\vec{n}$	$:=$	$\{$ empty, push, pop $\}$
$\vec{v}$	$\in$	$\mathcal{V}^*$
$\mathsf{Stack}_{\vec{w}}(\ \vec{n}\ )$		
Stack	$\stackrel{\text{def}}{=}$	$\mathsf{push}(x).\mathsf{Stack}_x + \overline{\mathsf{empty}}\langle\rangle.\mathsf{Stack}$
$\mathsf{Stack}_{v,\vec{w}}$	$\stackrel{\text{def}}{=}$	$\mathsf{push}(x).\mathsf{Stack}_{x,v,\vec{w}} + \overline{\mathsf{pop}}\langle v\rangle.\mathsf{Stack}_{\vec{w}}$

Unbounded Structures: Stacks (II)

- "implementation":
  using a **chain** of individual cells for the stored values
- cells can have one of the following states:
  - E: nothing is left in the stack accessible through this cell
  - C_v: a cell containing value v
  - D: nothing left in this particular cell,
    but maybe beyond D on "the right of it" ...

$\vec{n}$	:=	push, empty, pop, not, drop, pull
$X\langle\,\vec{n}\,\rangle \frown Y\langle\,\vec{n}\,\rangle$	:=	$(\boldsymbol{\nu}\, a, b, c)$
		$(\, X\langle\,\vec{n}\,\rangle[^{a,b,c}/_{\mathsf{not,drop,pull}}] \mid Y\langle\,\vec{n}\,\rangle[^{a,b,c}/_{\mathsf{push,empty,pop}}]\,)$
E	:=	$\mathsf{push}(x).(C_x \frown E) + \overline{\mathsf{empty}}\langle\rangle.E$
C_v	:=	$\mathsf{push}(x).(C_x \frown C_v) + \overline{\mathsf{pop}}\langle v\rangle.D$
D	:=	$\mathsf{pull}(x).C_x + \mathsf{drop}().E$
$S_{\vec{v}}$	:=	$C_{v_1} \frown \cdots \frown C_{v_n} \frown E$

- Calculate the states for the transition sequence $\xrightarrow{\mathsf{push}1} \xrightarrow{\mathsf{push}2} \xrightarrow{\mathsf{pop}2}$ and "stabilize" the remainder.
- Compare $\mathsf{Stack}_{\vec{v}}$ and $S_{\vec{v}}$ ...

A **Turing-machine** consists of:

- a finite alphabet of symbols
- an infinite tape
- a finite control mechanism
- movement or r/w-head to left or right

A Turing-machine can be nicely simulated with concurrent processes by two stacks (the tape). Neither an infinite alphabet nor infinite summation is necessary for this. [Milner 89]

1. The calculus of concurrent process expressions is *Turing-powerful*.
2. The halting problem for some "Turing machine" TM can be encoded as the *existence* of an infinite sequence $\mathsf{TM} \rightarrow^{\omega}$.

Unbounded Structures: Stacks (IV)

Some criticism:

- D's cannot be reused for storing *new* values (neither inner nor outer D's!).
- E's are never "used", pile up and stay around. (Note that, although $E \frown E$ "=" E, explicit garbage collection would be required.)

Unbounded Structures: Stacks (V)

E	:=	$\mathsf{push}(x).C_x + \overline{\mathsf{empty}}\langle\rangle.E$
C_v	:=	$\mathsf{push}(x).(C_x \frown C_v) + \overline{\mathsf{pop}}\langle v\rangle.D + \overline{\mathsf{not}}\langle v\rangle.D$
D	:=	$\mathsf{pull}(x).C_x + \mathsf{drop}().E + \mathsf{push}(x).C_x$
$S_{\vec{v}}$	:=	$C_{v_1} \frown \cdots \frown C_{v_n} \frown E$

- What are the problems of this "implementation"?

Although Turing-powerful, concurrent process expressions are, in some particular sense, not expressive enough:
it is not possible to *cut out unusable (=dead) cells* E.

If we had the possibility to *dynamically change the interconnection structure* among process components, then cells could *drop out* by connecting their left and right neighbors together.

One way to do this is the transmission of "*channels over channels*".

negative actions $\overline{a}\langle v\rangle$: *send name* v *over name* a.

positive actions $a(x)$: *receive any name, say* v*, over name* a *and "bind the result" to name* x.

Binding results in *substitution* of the formal parameter x by the actual parameter v.

polyadic communication $\overline{a}\langle\vec{v}\rangle$ and $a(\vec{x})$ ($\vec{x}$ pairwise different) *transmit many values at a time*.

Syntax Conventions

$\mathcal{N}$ names $a, b, c \ldots, x, y, z$

$\mathcal{A}$ actions $\pi \ ::= \ x(y) \ \mid \ \overline{x}\langle y\rangle \ \mid \ \tau$

- finite sequences $\vec{a}$ ...
- All values/variables/channels are just names. Parentheses usually indicate bindings. Angled brackets are often omitted.
- parametric processes with defining equations are modeled via the more primitive notion of replication and name-passing

Pi Calculus

Definition: The set $\mathcal{P}$ of π-calculus proc. exp. is defined (precisely) by the following syntax:

$$\begin{array}{rcl} P & ::= & M \ \mid \ P|P \ \mid \ (\boldsymbol{\nu} a)\, P \ \mid \ \boxed{!\, P} \\ M & ::= & \mathbf{0} \ \mid \ \boxed{\pi.P} \ \mid \ M + M \end{array}$$

We use P, Q, P_i to stand for process expressions.

- $(\boldsymbol{\nu} ab)\, P$ abbreviates $(\boldsymbol{\nu} a)\, (\boldsymbol{\nu} b)\, P$
- $\sum_{i\in\{1..n\}} \pi_i.P_i$ abbreviates $\pi_1.P_1 + \ldots + \pi_n.P_n$

$P = \overline{x}\langle z \rangle.P'$
$Q = x(y).Q'$
$R = \ldots z \ldots$

Assume that $z \notin \mathrm{fn}(P')$.

Depict the transition

$$(\boldsymbol{\nu} z)\,(\,P|R\,) \mid Q \;\rightarrow\; P' \mid (\boldsymbol{\nu} z)\,(\,R \mid [^{z}/_{y}]Q'\,)$$

as a flow graph (with scopes) and verify it using the reaction and congruence rules.

$$\begin{aligned}
\mathsf{Car}(\,\mathsf{talk},\mathsf{swch}\,) &\stackrel{\mathrm{def}}{=} \overline{\mathsf{talk}}.\mathsf{Car}\langle\,\mathsf{talk},\mathsf{swch}\,\rangle \\
\mathsf{Base}_i &\stackrel{\mathrm{def}}{=} \mathsf{talk}_i.\mathsf{Base}_i + \mathsf{give}_i(t',s').\overline{\mathsf{swch}_i}\langle t',s'\rangle.\mathsf{Idle}_i \\
\mathsf{Idle}_i &\stackrel{\mathrm{def}}{=} \mathsf{alrt}_i().\mathsf{Base}_i \\
\mathsf{Ctre}_i &\stackrel{\mathrm{def}}{=} \overline{\mathsf{give}_i}\langle\mathsf{talk}_{i\oplus 1},\mathsf{swch}_{i\oplus 1}\rangle.\overline{\mathsf{alrt}_{i\oplus 1}}\langle\rangle.\mathsf{Ctre}_{i\oplus 1} \\
\mathsf{Syst}_i &\stackrel{\mathrm{def}}{=} (\boldsymbol{\nu}\cdots)\Big(\,\mathsf{Car}\langle\,\mathsf{talk}_1,\mathsf{swch}_1\,\rangle \mid \mathsf{Base}_1 \mid \mathsf{Idle}_2 \mid \mathsf{Ctre}_1\,\Big)
\end{aligned}$$

□ Exercise: Observe that $\mathsf{Syst}_i \;(\stackrel{\tau}{\longrightarrow})^3\; \mathsf{Syst}_{i\oplus 1}$

Exercise: Overtaking Cars

A car $C\langle\,n,b,f\,\rangle$ on a road is connected to its back and front neighbor through b and f, respectively, while n just represents its identifier.

The road is assumed to be infinite, so we ignore any boundary problem, and it is static in the sense that no cars may enter or leave the road.

Define $C(\,x,b,f\,)$ such that a car may overtake another car. Beware of deadlocks and nested overtake attempts. You are not allowed to change the parameter x of instances of C.

$$\begin{aligned}
\mathsf{Car}(\,x,b,f\,) &\stackrel{\mathrm{def}}{=} \\
\mathsf{Fast}(\,x,b,f\,) &\stackrel{\mathrm{def}}{=} \\
\mathsf{Slow}(\,x,b,f,b'\,) &\stackrel{\mathrm{def}}{=}
\end{aligned}$$

LTS: Prefixes

actions $\quad \mu \;::=\; \tau \;\mid\; y\langle\vec{x}\rangle \;\mid\; \overline{y}\langle\vec{z}\rangle$

(TAU) $\tau.P \stackrel{\tau}{\longrightarrow} P$ $\qquad$ (OUT) $\overline{a}\langle\vec{b}\rangle.P \stackrel{\overline{a}\langle\vec{b}\rangle}{\longrightarrow} P$

(INP) $$\frac{\vec{b} \subseteq \mathcal{N}}{a(\vec{x}).P \stackrel{a\vec{b}}{\longrightarrow} [^{\vec{b}}/_{\vec{x}}]P} \text{ if } |\vec{b}| = |\vec{x}|$$

(COMM) $$\frac{P \stackrel{\overline{a}\langle\vec{b}\rangle}{\longrightarrow} P' \qquad Q \stackrel{a\vec{b}}{\longrightarrow} Q'}{P \mid Q \stackrel{\tau}{\longrightarrow} P' \mid Q'}$$

$$\text{(RES)}\ \frac{P \xrightarrow{\mu} P'}{(\boldsymbol{\nu} c)\,P \xrightarrow{\mu} (\boldsymbol{\nu} c)\,P'}\ \text{if } c \notin \mathrm{n}(\mu)$$

$$\text{(OPEN)}\ \frac{P \xrightarrow{(\boldsymbol{\nu}\vec{b})\,\overline{a}\langle\vec{z}\rangle} P'}{(\boldsymbol{\nu} c)\,P \xrightarrow{(\boldsymbol{\nu} c\vec{b})\,\overline{a}\langle\vec{z}\rangle} P'}\ \text{if } \vec{z} \ni c \notin \{a, \vec{b}\}$$

The label on transition $\xrightarrow{(\boldsymbol{\nu}\vec{b})\,\overline{a}\langle\vec{z}\rangle}$ is called *bound output*.
(Invariant: $\vec{b} \subset \vec{z} \wedge a \notin \vec{b}$.)

$$\text{(PAR)}\ \frac{P \xrightarrow{\mu} P'}{P \,|\, Q \xrightarrow{\mu} P' \,|\, Q}\ \text{if } \mathrm{bn}(\mu) \cap \mathrm{fn}(Q) = \emptyset$$

$$\text{(CLOSE)}\ \frac{P \xrightarrow{a\,\vec{b}} P' \qquad Q \xrightarrow{(\boldsymbol{\nu}\vec{c})\,\overline{a}\langle\vec{b}\rangle} Q'}{P \,|\, Q \xrightarrow{\tau} (\boldsymbol{\nu}\vec{c})\,(P' \,|\, Q')}\ \text{if } \{\vec{b}\} \cap \mathrm{fn}(P) = \emptyset$$

LTS: Miscellaneous

$$\text{(SUM)}\ \frac{P \xrightarrow{\mu} P'}{P + Q \xrightarrow{\mu} P'}$$

$$\text{(REP)}\ \frac{P \,|\, !\,P \xrightarrow{\mu} P'}{!\,P \xrightarrow{\mu} P'}$$

$$\text{(ALP)}\ \frac{Q \xrightarrow{\mu} Q'}{P \xrightarrow{\mu} Q'}\ \text{if } P =_\alpha Q$$

Recursion

$A(\,\vec{x}\,) \stackrel{\text{def}}{=} Q_A$, where $Q_A \stackrel{\text{def}}{=} \cdots A\langle\,\vec{u}\,\rangle \cdots A\langle\,\vec{v}\,\rangle \cdots$
can be used in: $P \stackrel{\text{def}}{=} \cdots A\langle\,\vec{y}\,\rangle \cdots A\langle\,\vec{z}\,\rangle \cdots$

can be modeled through:

1. invent a to stand for A
2. for any R,
   let $\widehat{R}$ denote the result of replacing any call $A\langle\,\vec{w}\,\rangle$ by $\overline{a}\langle\vec{w}\rangle.\mathbf{0}$
3. replace P by

$$(\boldsymbol{\nu} a)\,(\,\widehat{P} \,|\, !\,a(\vec{x}).\widehat{Q_A}\,)$$

$\mathsf{True}(\,l\,) \stackrel{\text{def}}{=} l(t,f).\overline{t}\langle\rangle$

$\mathsf{False}(\,l\,) \stackrel{\text{def}}{=} l(t,f).\boxed{}$

$\mathsf{If}(\,l,\mathsf{foo},\mathsf{bar}\,) \stackrel{\text{def}}{=} (\boldsymbol{\nu} tf)\,\overline{l}\langle t,f\rangle.\big(\ \boxed{} + \boxed{}\ \big)$

Check that for all P, Q:

$(\boldsymbol{\nu} l)\,\big(\mathsf{True}\langle\,l\,\rangle \mid \mathsf{If}\langle\,l,\mathsf{foo},\mathsf{bar}\,\rangle\big)$ "=" $\boxed{}$

$(\boldsymbol{\nu} l)\,\big(\mathsf{False}\langle\,l\,\rangle \mid \mathsf{If}\langle\,l,\mathsf{foo},\mathsf{bar}\,\rangle\big)$ "=" $\boxed{}$

$[\![\,\overline{y}\langle\vec{z}\rangle.P\,]\!] \stackrel{\text{def}}{=}$

$[\![\,y(\vec{x}).P\,]\!] \stackrel{\text{def}}{=}$

Think about:

$\overline{y}\langle z_1, z_2\rangle.P \mid y(x_1,x_2,x_3).Q$

$\rightarrow$

$\overline{y}\langle z_1, z_2\rangle.P \mid y(x_1,x_2).Q \mid \overline{y}\langle w_1, w_2\rangle.R$

$\rightarrow$

$[\![\,\overline{y}\langle\vec{z}\rangle.P\,]\!] \stackrel{\text{def}}{=}$

$[\![\,y(\vec{x}).P\,]\!] \stackrel{\text{def}}{=}$

Encoding Synchrony

$[\![\,P_1 \mid P_2\,]\!] \stackrel{\text{def}}{=} [\![\,P_1\,]\!] \mid [\![\,P_2\,]\!]$

$\vdots$

$[\![\,\overline{y}\langle z\rangle.P\,]\!] \stackrel{\text{def}}{=}$

$[\![\,y(x).P\,]\!] \stackrel{\text{def}}{=}$

Encoding Summation

$P \ ::= \ \ldots \ \mid \ \sum_{i\in I} y_i(x).P_i \ \mid \ \mathsf{if}\ x\ \mathsf{then}\ P\ \mathsf{else}\ P$

$[\![\,\sum_{i\in I} y_i(x).P_i\,]\!] \stackrel{\text{def}}{=}$

$[\![\,y(x).P\,]\!] \stackrel{\text{def}}{=}$

$$[\![\, x \,]\!](\, u \,) \stackrel{\text{def}}{=} \overline{x}\langle u \rangle$$

$$[\![\, \lambda x\, M \,]\!](\, u \,) \stackrel{\text{def}}{=} u(x, v).[\![\, M \,]\!]\langle\, v \,\rangle$$

$$[\![\, (MN) \,]\!](\, u \,) \stackrel{\text{def}}{=} (\boldsymbol{\nu} v)\ \Big(\ [\![\, M \,]\!]\langle\, v \,\rangle \mid (\boldsymbol{\nu} x)\, \overline{v}\langle x, u \rangle \mid \mathbf{!}\, x(u).[\![\, N \,]\!]\langle\, u \,\rangle\ \Big)$$

Try to evaluate/encode $(\cdots((M_0 N_1) N_2)\cdots)$

name-passing vs. **value-pasing**

- ☐ better pragmatics
- ☐ natural programming idioms
- ☐ semantic foundations for all (?) major programming styles
- ☐ ...
- ☐ security protocols via (s)pi-calculus
  ($\rightarrow$ research at LAMP2 ...)